# RECTANGULAR POCKET ADJUSTABLE ACCENT LIGHT

## 1005-2LEDZ-FH-VHO

Dual lamp, solid state light engine, recessed, flanged open slot accent light with residential, commercial and retail applications. Suitable for new construction. Can

nominal 6" x 12" rectangular aperture. Accent and downlighting typically found in be used in surfaces such as wood, stone, etc.

## **SPECIFICATIONS**

### **HOUSING**

· Extruded aluminum with bolt on end plates and integral flange

### MOUNTING

· Recessed in architectural ceiling

## **ELECTRICAL**

Integral dimmable electronic driver with internal short circuit protection

• (2) Citizen LEDs supplied with fixture

### SOCKET

· Precision aluminum yoke with CNC machined lampholder assembly

- · Interchangeable reflector provides multiple beam patterns
- · Solite, Veiling Acrylic available as standard. For more options, consult factory


· Flanged housing


### **FINISH**

- · Powder paint on all surfaces in black and white as standard
- · Additional colors and RAL palette available
- · Consult factory for custom finishes


## **LABELS**

• (I) US tested to UL standards 1598, Damp location









# ORDERING INFORMATION

6 <sup>13</sup>/<sub>16</sub>" [173 mm]

7" [178 mm]

1005-2LEDZ-FH-VHO	SOURCE / DRIVER	BEAMSPREAD	TRIM / FINISH	LAMP LENS	ACCESSORIES
	I		1		
Flanged Housing 9 = 90+CRI 27 = 2700K 30 = 3000K 35 = 3500K 40 = 4000K	CZ14=120-277v, 14W 1450Im CZ20=120-277v, 20W 2000Im CZ28*=120-277v, 28W 2675Im C1=0-10V dimming, 1%, 120-277v C2=TRIAC/ELV 2-wire, 1% 120v (Lead/Trail Edge) E1=EldoLED 0-10V Logarithmic Dim, 0.1%, 120-277v E2=EldoLED DALI, 0.1%, 120-277v E3=EldoLED 0-10V Linear Dim, 0.1%, 120-277v L2=Lutron Hi-lume 1% 2-wire LED driver (120v forward phase) LTB=Lutron Hi-lume 1% EcoSys LED driver, 1%, 120-277v, Soft-on, Fade-to-Black	10 = 10 Degrees 20 = 20 Degrees 30 = 30 Degrees	P14 = White BLK=Black ANA = Clear Aluminum CST = Custom	Blank = None 79A=Veiling Acrylic 91A = Solite 93A = Frosted	97L = Black Hexcell

\*Contact Factory to request separate cutsheet

